

Product sheet

FERMAX 3266 WIBOX Mobile Call Forwarding

Brand: FERMAX

Reference: FERMAX 3266



Mobile call forwarding from the FERMAX Wi-box WIBOX device is a small module that allows you to connect one or more mobiles to your home's VDS monitor or phone by simply downloading the App and pairing it with your wifi. Perform all the functions you do from your VDS phone without even being at home

[View product online](#)

Description

FERMAX 3266 WIBOX mobile call forwarding Wi-Box is a WiFi device with VDS technology that allows you to divert calls received on the VDS monitor or phone from the home to your mobile phone through an app. You only need to download the Fermax Wi-Box application, available for free in the Play Store and App Store and pair it with the Wi-Box module. It is physically installed near the VDS terminal, in parallel and acts as one more terminal, and through the Wi-Box application it is possible to remotely perform the functions you do from the terminal of the house, and many more! for everyone from anywhere.

TECHNICAL SPECIFICATIONS

Product dimensions (Width x Height x Depth mm): 80 x 80 x 20 mm./3.14 x 3.14 x 0.78 inches

Connectivity: Wifi (2.4 Ghz)

Date and time: 24h autonomy without power

Supply voltage: 18 Vdc (the module is powered directly from the terminal)

Maximum consumption: 2.7 W

Standby consumption (paired and connected): 1.8 W

Operating temperature (°C): Humidity: [-5 ° C, + 40 ° C]; [0%, 90%]

Product weight (kg): 0.097

Line adapter: Yes. 75 Ohm resistor included for video impedance adjustment (V, M)

Cable terminals with molex connector: +, L, -, V, M, Ct, F1

What can you do with Wi-box

RECEPTION CALLS. CONVERSATION: Speak or mute the microphone

DOOR OPENING Opening of the main door. AUTO START. SWITCH PLATE OR CHAMBER Main, secondary or auxiliary camera display

CAPTURE OF PHOTOS Image capture No limit during the conversation or before answering

VIDEO CAPTURE Record video with a maximum duration of 90 seconds per conversation.

CALL TO CONSERJE If the building has a concierge, you can call it from your mobile and wait for it to be answered

ACTIVATE ADDITIONAL FUNCTION Opening a secondary door or turning on lights.

Specifications

EAN	8424299032665
Manufacturer	FERMAX

This document is based on the product page published in our store and is provided for information only. It is not contractual. It may contain errors or omissions and does not replace the manufacturer datasheet.

[If you have any questions, contact our support team](#)

Item downloaded on 26 October 2026