Product sheet



64-unit dimmer DALI button registration box

Brand: DINUY

Reference: DINUY RE PLA DA1

• Dimmer, in tablet format, to control fluorescent or LED luminaires, with Ballast or Driver dimmable by DALI signal.
• Broadcast communication with DALI equipment.
• Possibility of controlling up to 64 DALI devices.
• Control by means of a conventional button: short presses turn on/off and long presses dim.
• Memory function.
• Flush mounting in a junction box.

View product online

Description

Product reference RE PLA DA1
Supply Voltage (V) 230VAC
Frequency (Hz) 50/60
Own Consumption < 3W
Output Channels 1
Maximum power (VA) 0
Load Type Ballast or DALI Driver
Maximum absorption current per 1/10V (mA) 0
Maximum number of devices 64
Button control
Maximum number of illuminated pushbuttons 0
No. of modules 0
Type of connection terminals Captive screws
Cable section (mm2) 2.5Storage temperature (ºC) (min) -30
Storage temperature (ºC) (max) 70
Installation Registration box
Operating temperature (ºC) (min) 0
Operating Temperature (ºC) (max) 40

Environmental Protection IP20 according to UNE 20324
According to the Low Voltage Directives 2014/35/EU; Electromagnetic Compatibility 2014/30/EU; 2011/65/EU
In accordance with the UNE-EN 60669-1:2018 Standard; UNE-EN 60669-2-1:2005, +erratum:2008, +/A1:2010, +/A12:2011; UNE-EN 60669-2-3:2007

Specifications

EAN	8422447015591
Manufacturer	Dinuy

This document is based on the product page published in our store and is provided for information only. It is not contractual. It may contain errors or omissions and does not replace the manufacturer datasheet.

If you have any questions, contact our support team

Item downloaded on 4 November 2026