Product sheet

# Ladder timer for register box Orbis Tempo led OB200007

Brand: ORBIS

Reference: ORBIS OB200007



Timer for recessed mounting in box universal.
Installation two-wire without neutral.
Valid for LED lamps.

Timing the ignition for lighting installations in: stairs, corridors, lobbies, garages, basements, storage rooms, bathrooms, etc

View product online

## Description

Timer ladder for box of registry Orbis Tempo led OB200007

Small size for installation between the pushbutton and the mechanism box, is hidden in logs, false ceiling, etc

Quick installation without works or neutral connection.

Compatible with any pushbutton from the market.

Reduction of energy consumption in lighting and increase of the useful life of the lamps.

Valid for any lamp, except LED with transformer electromagnetic and all types of fluorescence.

Timing of 15 s to 15 min rearmable.

Supports push-buttons additional.

Allows control of fans and pumps.

Thermal protection and short-circuit built-in.

Power Supply: 230 Vac

Nominal frequency: 50 Hz

Own consumption: 0,035 WILL

Rearmable: If

Timing range: 15 seconds - 15 min.

Protection: Short circuit, over-current.

Degree of protection: IP 20 according to en 60529.

Operating temperature: -10 to + 50 ° C

Built-in thermal protection.

**Maximum loads:**

Incandescent: 150 W.
Fluorescent: Not Suitable.
Halogen low voltage ( electronic transformer): 100 VA.
Halogen low voltage ( transformer electromagnetic): 100 VA.
Halogen (230 Vac In): 150 W.
Lamps low consumption: Not Suitable.
LED lamps ( electronic transformer): 100 VA.
LED lamps ( transformer electromagnetic): Not Suitable.
Fans. 50 VA.

## Specifications

| | |
|---|---|
| EAN | 8426709113131 |
| Manufacturer | Orbis |
| Protection | IP20 |
| Nominal voltage (V) | 230V |
| Type of installation | Hidden |

This document is based on the product page published in our store and is provided for information only. It is not contractual. It may contain errors or omissions and does not replace the manufacturer datasheet.

If you have any questions, contact our support team

Item downloaded on 4 November 2026