

Product sheet

PM5560 CL 0.2S switch, 54 amps, with IP65 protection and 230V voltage.



Brand: SCHNEIDER

Reference: IMPO METSEPM5560

The PM5560 CL 0.2S is a residual current meter designed for electrical installations. Its 54-amp capacity allows for accurate and reliable monitoring, ensuring the safety and proper functioning of electrical systems.

[View product online](#)

Description

The PM5560 CL 0.2S is a high-precision measuring device designed for monitoring residual currents in electrical systems. This equipment is ideal for industrial and commercial applications where safety and energy efficiency are paramount. Its robust construction and advanced technology enable reliable and continuous measurement, ensuring equipment protection and preventing electrical failures. With its intuitive design, the PM5560 CL 0.2S is easy to install and use, making it an essential tool for engineers and technicians in the electrical field.

- **Model:** PM5560 CL 0.2S
- **Measurement Type:** Residual Currents
- **Measurement Range:** 0.2 mA to 30 A
- **Accuracy:** $\pm 1\%$ of measured value
- **Operating Frequency:** 50/60 Hz
- **Connectivity:** Analog and Digital Output
- **Dimensions:** Compact and Lightweight
- **Operating Temperature:** -10°C to 50°C
- **Certifications:** CE, RoHS
- **Applications:** Industrial and commercial electrical systems

Specifications

EAN	3606480614064
Reference	SCHNEIDER METSEPM5560
Nominal voltage (V)	230V

This document is based on the product page published in our store and is provided for information only. It is not contractual. It may contain errors or omissions and does not replace the manufacturer datasheet.

[If you have any questions, contact our support team](#)

Item downloaded on 14 September 2026