

Product sheet



LECTOR PROXIMIDAD DESFIRE CITY

Brand: FERMAX

Reference: FERMAX 6957

Lector que permite la apertura de la puerta al acercar una tarjeta o llavero de proximidad. Sólo las tarjetas o llaveros autorizados accionarán el dispositivo. No es necesario un contacto físico. Lector de proximidad que mediante una configuración de dipswitches que incorpora puede funcionar en un sistema autónomo o centralizado. Configuración como AUTÓNOMO. Capacidad de hasta 400 tarjetas o llaveros de usuarios. Lector y controlador integrados en el mismo módulo. Configuración como CENTRALIZADO con protocolo Wiegand 26 o Data/Clock.(Compatible AC-MAX) Módulo de control de accesos, para incorporar en placas de portero/videoportero SKYLINE y CITYLINE. Recomendado para interiores y exteriores. Identificadores compatibles con tarjetas y llaveros DESFIRE EV2 marca FERMAX Tensión alimentación 12 Vdc Consumo en reposo 45 mA Consumo relé activo 85 mA Temperatura funcional -15°C a + 55°C Humedad relativa 5-95% (sin condensación) IP 43 IK 07

[View product online](#)

Specifications

High	7,3
Width	14,8
EAN	8424299069579
Depth	13,8

This document is based on the product page published in our store and is provided for information only. It is not contractual. It may contain errors or omissions and does not replace the manufacturer datasheet.

[If you have any questions, contact our support team](#)

Item downloaded on 16 September 2026