

Product sheet

LEDME 20-50W Emergency Conversion Kit with Battery

Brand: LEDME

Reference: LEDME LM2129



The Emergency Conversion Kit M LEDME operates with maximum power between 20 and 50 watts, operating in a thermal range of -0°C to +50°C. Its compact 213x40x28H design uses PC material and features 11.1V 2600mAh battery.

[View product online](#)

Description

The M LEDME Emergency Conversion Kit is a device designed to provide backup lighting in situations where the main power fails, operating with a maximum adjustable power between 20 and 50W.

Technical characteristics

- Mark: M LEDME
- Maximum power: 20 to 50W
- Working temperature: -0°C ~ +50°C
- Protection: IP30
- Power supply: 85-265v ac
- Battery: 11.1v 2600 mah
- Dimension: 213X40X28H mm
- Material: PC
- Load Time: 24 h
- Time of use: 180 m
- Guarantee: 3 years

Thanks to its high capacity battery and wide input voltage range, this equipment ensures stable operation in various electrical conditions.

Specifications

Timer	No
High	28
EAN	8435579721292
Manufacturer	Ledme
Long	213
Remote control	No
Measures	213x40x28H mm
Power (W)	50
Depth	40
Protection	IP30
Adjustable	No
Nominal voltage (V)	85-265
Current type	AC

This document is based on the product page published in our store and is provided for information only. It is not contractual. It may contain errors or omissions and does not replace the manufacturer datasheet.

If you have any questions, contact our support team

Item downloaded on 29 September 2026